

MX-15

AC & 12V DC Operation

DESCRIPTION :

The Ahuja MX-15 is a PA analog mixer. 4 Line outputs for connecting a number of Amplifiers or Boosters.

All inputs with On/Off switches with LED display.



FEATURES :

- General Purpose 12 Channel PA Mixer Preamplifier
- 12 Mic & 3 Aux Inputs.
- All inputs with On/Off switches with LED display.
- Master control for overall adjustment.
- 4 Line outputs for connecting a number of Amplifiers or Boosters.
- Headphone output for monitoring.
- Active Bass and Treble tone controls.

SPECIFICATIONS :

Power Requirement	AC: 220-240v 50/60Hz, DC: 12V (1×12V Car Battery)
Outputs	2 × Preamp 200mV/600Ohm, 4 × Line 1V/1kOhm, 1 × Headphone 120mV@ 8Ohm
Frequency Response	20-20,000Hz (±3dB)
Distortion	< 1%
Signal to Noise Ratio	50dB
Input Channels	12 × Mic 0.6mV/4.7kOhm, 2 × Aux 100mV/470kOhm, 1 × Aux 500mV/100kOhm
Tone Controls	Bass: ± 10dB at 100Hz, Treble: ± 10dB at 10kHz
Dimensions	W350 × H145 × D200 mm
Weight	3.9kg

Specifications from the official Ahuja catalogue. Issued for customer reference.