

SSA-5000EM

High Wattage PA Mixer Amplifier



FEATURES :

- Preamplifier and Line Output for connecting to a Booster Amplifier and for recording the programme.
- Resettable circuit breaker for protection against overload and short circuit.
- Instant transfer to DC power (Car Battery) if AC power fails.

SPECIFICATIONS :

Power Output	750W Max., 500W RMS at 10% THD, 450W RMS at 5% THD, 415W RMS at 2% THD
Output Regulation	2 dB, no load to full load at 1kHz
Input Channels	7 × Mic 0.8mV/4.7kOhm, 2 × Aux 100mV/470 kOhm, 1 × Line 1V/50kOhm
Frequency Response	50-15,000Hz ±3dB
Signal to Noise Ratio	60dB
Tone Controls	Bass: ±10dB at 100Hz, Treble: ±10dB at 10kHz
Outputs	Preamp 200mV/600Ohm, Line 1V/1kOhm
Speaker Outputs	4Ohm, 8Ohm, 70V & 100V
Power Supply	AC: 220-240V 50/60Hz DC: 36V (3×12V Car Battery)
Power Consumption	AC: 1000VA DC: 8A
Dimensions	W510 × H172 × D385 mm
Weight	26.7kg

Specifications from the official Ahuja catalogue. Issued for customer reference.