

TZA-1500DP

160 WATTS WITH BUILT-IN DIGITAL PLAYER

DESCRIPTION :

The Ahuja TZA-1500 DP is a PA mixer amplifier. It has a choice to connect both the zones to 100V (LMT) type speakers, or 100V speakers to one zone and low impedance type speakers to the other zone.

Both the zones can also be connected to low impedance type speakers. Built-in MP3 player with remote control for USB, SD/MMC card reader.



FEATURES :

- 6 Mic, 2 Aux Inputs.
- Built-in MP3 player with remote control for USB, SD/MMC card reader.
- Preamplifier and Line Output for connecting to a Booster Amplifier and for recording the programme.
- TZA-1500DP is ideal for medium sized installations such as in places of worship where two separate groups of speakers are needed to be connected.
- User has a choice to connect both the zones to 100V (LMT) type speakers, or 100V speakers to one zone and low impedance type speakers to the other zone. Both the zones can also be connected to low impedance type speakers.
- Instant transfer to DC power (Car Battery) if AC power fails.

SPECIFICATIONS :

Power Output	100W + 100W Max., 80W + 80W RMS at 10% THD, 70W + 70W RMS at 5% THD
Output Regulation	2 dB, no load to full load at 1kHz
Input Channels	6 × Mic 0.6mV/4.7kOhm, 2 × Aux 100mV/470kOhm
Frequency Response	65-15,000Hz ±3dB
Signal to Noise Ratio	60dB
Tone Controls	Bass: -10dB at 100Hz, Treble: -10dB at 10kHz
Output	Preamp 200mV/600Ohm, Line 1V/1kOhm
Speaker Output	4Ohm, 8Ohm, 70V & 100V
Digital Player	MP3 Player with USB, SD and MMC Card Reader
Power Supply	AC: 220-240V 50/60Hz DC: 12V (12V Car Battery)
Power Consumption	AC: 300VA DC: 6A
Dimensions	W460 × H155 × D310 mm

Weight

14.5kg

Specifications from the official Ahuja catalogue. Issued for customer reference.