

APZ-502CU

Paging Selector Control Unit

DESCRIPTION :

10 Zone Paging selector / controller.



FEATURES :

- 10 Zone Paging selector / controller.
- Provision for connecting APZ-501RM for paging from separate location.
- Provision also for connecting an additional microphone and doing zonal paging from the Paging Selector itself. These announcements will have priority over announcements made from a Remote Paging Microphone.
- 2 channel amplifier inputs (Channel A for BGM Amplifier and Channel B for Paging Amplifier). When paging announcement is made, music will be interrupted only in zones where announcement is required.
- Two color zone status LEDs to indicate music or paging status of each zone.
- Provision to cascade upto 30 sets of APZ-502CU for a 300 zone system.

SPECIFICATIONS :

Input	MIC 1 and 2: 600Ohm, 5mV unbalanced; Line 1 and 2: 10kOhm, 775mV unbalanced
Frequency Response	MIC 100Hz-15kHz; Line 30Hz-18kHz
S/N Ratio	MIC 60dB; Line 80dB
Controls	MIC 1 and 2 volume, 10 channel selectors, chime button, power
Power Supply	230V / 50Hz
Communication Protocol	RS422
Communication Input and Speed	RJ45, 4800 bps
Dimensions	W484 × H88 × D303 mm
Weight	4.6 kg

Specifications from the official Ahuja catalogue. Issued for customer reference.