

BTA-880

PA Amplifier Set



FEATURES :

- Two Mic inputs, Two Wireless Mics, one Aux input & one Music input. Mic1 has selectable priority over all other inputs.
- Built-in 30.4 cm (12") 4Ohm speaker & 8Ohm HF driver.
- Tone control for setting the desire tonal quality.
- LED indications for low battery, charging & clip output. Auto cut-off feature prevents deep discharge of rechargeable battery.
- Operates on AC mains, external 12V DC or built-in 12V 7Ah rechargeable battery.

SPECIFICATIONS :

Speaker	1x12" Speaker, 1xHF Driver
Power Output (BI-Amp)	50W Max. (LF+HF) LF: 35W Max HF: 15W Max
Input Channels	2 x Mic 3mV/4.7kOhm, 1 x Aux 100mV/47kOhm, Music 100mV/47kOhm, 2 x Wireless
Frequency Response	55-18,000Hz $\pm$ 3dB (Bi-Amp)
S/N Ratio	60dB
Tone Controls	Bass $\pm$ 5dB at 100Hz, Treble $\pm$ 5dB at 10kHz
Digital Player	MP3 player with USB, SD, MMC card reader, Recording function and Bluetooth
Preamp Output	200mV/600Ohm
Protections	AC Fuse: 1 Amp. 250V (T 1A L)
Power Supply	AC : 220V-240V 50/60Hz, DC : 12V Car Battery (external), 12V 7Ah Rechargeable
AC Power Consumption	60VA
Dimensions	W405 x H610 x D350 mm
Weight	18.80 kg
Wireless Microphone	2 x Hand Held
Frequency Stability	$\pm$ 0.005%
Max. Modulation	45dB

RF Output	10mW
Battery	3V (2 × 1.5V AA Pencil Cells)
Current Consumption	< 200mA
Weight (w/o battery)	140g

Specifications from the official Ahuja catalogue. Issued for customer reference.