

DA-88

PA Audio Splitter

DESCRIPTION :

The Ahuja DA-88 is a PA audio splitter. Provides four stereo balanced outputs or eight mono balanced outputs through M/XLR connectors.

Accepts Line Level Stereo as well as Mono inputs through F/XLR connector as well as 6.3mm (1/4") stereo phone jack sockets.



FEATURES :

- Compact and rugged professional line level signal splitter.
- Designed for use in a wide variety of indoor and outdoor PA applications.
- Accepts Line Level Stereo as well as Mono inputs through F/XLR connector as well as 6.3mm (1/4") stereo phone jack sockets.
- Provides four stereo balanced outputs or eight mono balanced outputs through M/XLR connectors.
- Individual volume control for each input & output channel.
- Separate clip LED indicator for Left and Right input signal.
- Easy to operate Stereo/Mono push switch, provided on front panel.
- Operates on AC mains.
- 19" rack mountable in 1U size and usable as a table top unit also.

SPECIFICATIONS :

Input Channels	2 × 100mV/20kOhm Balanced
Outputs	8 × 1V / 50Ohm Balanced
Frequency Response	20-20,000Hz ±3dB
Distortion	<0.1%
Signal to Noise Ratio	70dB
Power Supply	AC: 220-240V 50/60Hz
Dimensions	W483 × H52 × D195 mm
Weight	2.80kg

Specifications from the official Ahuja catalogue. Issued for customer reference.