

FMX-106DP

With built-in MP3 Player & Digital Effects



FEATURES :

- Each channel has a GAIN control for optimum adjustment of the MIC & LINE input sensitivities.
- Active BASS & TREBLE controls in each channel for desired equalisation of the input signal.
- Separate FX (effects) level control for each input channel.
- MP3 digital player with recording, playback through USB & Bluetooth facility.
- Stereo input channel is provided with a GAIN control, 2 band EQ, FX & LEVEL Controls.
- Built-in digital effects processor with DELAY, REPEAT and LEVEL controls.
- Line level LEFT & RIGHT outputs through 6.3 mm (1/4") stereo jack sockets.
- Individual SIGNAL & CLIP LEDs for optimum setting of signal levels.

SPECIFICATIONS :

MIC Input (Impedance/Gain)	2kOhm Balanced/65dB, 1kOhm Unbalanced/65dB
LINE Input (Impedance/Gain)	20kOhm Balanced/45dB, 10kOhm Unbalanced/45dB
Distortion	< 0.1%
Frequency Response	25Hz-20 kHz (-1dB)
Tone Controls	Line Output HI: 0dBu/+21dBu (775mV/9V)
Delay System	Digital Signal Processing
Delay Range Settings	Variable from 20 to 300ms
Digital Player	MP3 Player/Recorder with USB Reader, Bluetooth
Signal to Noise Ratio	> 68dB
Power Supply	AC: 220-240v 50/60Hz
Dimensions	W281 x H75 x D210 mm
Weight	1.60kg

Specifications from the official Ahuja catalogue. Issued for customer reference.