

SSA-10000

High Wattage PA Mixer Amplifier



FEATURES :

- 8 Mic & 4 Aux Inputs.
- Aux-4 input is through RCA socket specially for connecting CD/DVD player.
- Preamplifier and Line Output for connecting to a Booster Amplifier and for recording the programme.
- Resettable circuit breaker & MCB at back for protection against overload and short circuit.
- Instant transfer to DC power (Car Battery) if AC power fails.

SPECIFICATIONS :

Power Output	1350W Max., 1000W RMS at 10% THD, 850W RMS at 5% THD, 800W RMS at 2%
Output Regulation	2 dB, no load to full load at 1kHz
Input Channels	8 × Mic 0.8mV/4.7kOhm, 3 × Aux 100mV/50 kOhm, 1 × Aux 250mV/50 kOhm, 1 ×
Frequency Response	50-15,000Hz ±3dB
Signal to Noise Ratio	60dB
Tone Controls	Bass: ±10dB at 100Hz, Treble: ±10dB at 10kHz
Outputs	Preamp 200mV/600Ohm, Line 1V/1kOhm
Speaker Outputs	2Ohm, 4Ohm, 70V & 100V
Power Supply	AC: 220-240V 50/60Hz DC: 48V (4×12V Car Battery)
Power Consumption	AC: 1600VA DC: 12A
Dimensions	W540 × H185 × D510 mm
Weight	42.0kg

Specifications from the official Ahuja catalogue. Issued for customer reference.