

SSB-85FX

MEDIUM WATTAGE PA MIXER AMPLIFIER

FEATURES :

- Built-in digital echo effect on Mic-4.
- Mic-3 is alternate to Aux through switch.
- Mic-1 & Mic-2 having LO-CUT facility.
- Cut type Bass & Treble controls.



SPECIFICATIONS :

Power Output	110W Max., 80W RMS at 10% THD, 75W RMS at 5% THD, 60W RMS at 2% THD
Output Regulation	2 dB, no load to full load at 1kHz
Input Channels	4×Mic 0.65mV/4.7kOhm, 1 × Aux 100mV/470kOhm
Frequency Response	65-15,000Hz ±3dB
Signal to Noise Ratio	60dB
Tone Controls	Bass: -10dB at 100Hz, Treble: -10dB at 10kHz
Outputs	Preamp 200mV/600Ohm
Speaker Outputs	4Ohm, 8Ohm, 16Ohm, 70V & 100V
Power Supply	AC: 220-240V 50/60Hz, DC: 12V (12V Car Battery)
Power Consumption	AC: 180VA DC: 3A
Dimensions	W355 × H133 × D285 mm
Weight	8.5kg

Specifications from the official Ahuja catalogue. Issued for customer reference.