

TZA-4000DPM

400 WATTS WITH BUILT-IN DIGITAL PLAYER

DESCRIPTION :

The Ahuja TZA-4000 DPM is a PA mixer amplifier with stereo/mono switch to change ambience of MP3 music player and cd/stereo music for dj programmes.

Built-in MP3 player with remote control and LCD display for USB, SD/MMC card reader.



FEATURES :

- 6 Mic, 2 Aux Inputs and CD/Stereo input (L&R).
- Built-in MP3 player with remote control and LCD display for USB, SD/MMC card reader.
- Stereo/Mono switch to change ambience of MP3 music player and CD/Stereo music for DJ programmes.
- Separate USB level control provided.
- Line Input & Output on each zone for connecting to a Mixer and Booster Amplifier respectively. Preamplifier output for recording.
- Box Speaker/Driver Unit selector switch for each zone. Bass boost defeated at Driver Unit position for safer operation of driver units. Zone On/Off facility.
- Resettable circuit breaker for protection against overload and short circuit.
- Instant transfer to DC power (Car Battery) if AC power fails.

SPECIFICATIONS :

Power Output	300W + 300W Max., 200W + 200W RMS at 10% THD, 180W + 180W RMS at 5%
Output Regulation	2 dB, no load to full load at 1kHz
Input Channels	Mic/Aux: 6 × Mic 0.6mV/4.7kOhm, 2 × Aux 100mV/470kOhm, Stereo Music Mode:
Frequency Response	50-15,000Hz ±3dB
Signal to Noise Ratio	60dB
Tone Controls	Bass: ±10dB at 100Hz, Treble: ±10dB at 10kHz
Output	Preamp 200mV/600Ohm, Line 1V/1kOhm
Speaker Output	4Ohm, 8Ohm, 70V & 100V for each zone
Digital Player	MP3 Player with USB, SD and MMC Card Reader
Power Supply	AC: 220-240V 50/60Hz DC: 24V (2×12V Car Battery)
Power Consumption	AC: 700VA DC: 9A

Dimensions	W510 × H172 × D385 mm
------------	-----------------------

Weight	24.2kg
--------	--------

Specifications from the official Ahuja catalogue. Issued for customer reference.