AHUJA®
PUBLIC ADDRESS SOLUTIONS
Hallmark of Reliability!

UB-30M

LOW WATTAGE PA MIXER AMPLIFIER

DESCRIPTION :

The Ahuja UB-30M is a 25W low wattage PA mixer amplifier with AC and 12V DC operation.

Features 2 mic and 1 aux input, cut type tone control, and automatic changeover from AC to battery operation.



FEATURES :

- AC & 12V DC operation - 2 power source amplifier.
- 2 mic and 1 aux input.
- Cut type tone control.
- Provision of automatic changeover from AC to battery operation ensuring continuity of program.
- Protection against wrong battery polarity.

SPECIFICATIONS :

Power Output	30W RMS Max., 25W RMS at 10% THD
Input Channels	2 × Mic 1.0mV/4.7kOhm, 1 × Aux 100mV/470kOhm
Frequency Response	150-10,000Hz ±3dB
Signal to Noise Ratio	60dB
Tone Controls	-10dB at 10kHz
Speaker Outputs	4Ohm, 8Ohm & 16Ohm & 100V
Power Supply	AC: 220-240V 50/60Hz, DC: 12V (Car Battery)
Power Consumption	AC: 80VA DC: 1.2A
Dimensions	W180 × H80 × D260 mm
Weight	3.00kg

Specifications from the official Ahuja catalogue. Issued for customer reference.