

# UBA-500M

## DJ & PA POWER AMPLIFIER

**DESCRIPTION :**

The Ahuja UBA-500M is a 500W dj and PA power amplifier. UBA-500M is a 500 Watts amplifier which can be connected to various input sources like a Microphone, PA Mixer, DJ Mixer, CD Player, Cassette Player, Keyboard etc.

The amplifier includes an built-in 5 Band Graphic Equalizer with tone ON/OFF switch which enables precise and accurate tonal setting of the programme.



## FEATURES :

- Designed for use in a wide variety of PA applications and DJ performances.
- UBA-500M is a 500 Watts amplifier which can be connected to various input sources like a Microphone, PA Mixer, DJ Mixer, CD Player, Cassette Player, Keyboard etc.
- The amplifier includes an built-in 5 Band Graphic Equalizer with tone ON/OFF switch which enables precise and accurate tonal setting of the programme.

### SPECIFICATIONS :

|                       |                                                                                                   |
|-----------------------|---------------------------------------------------------------------------------------------------|
| Power Output          | 650W RMS Max., 500W RMS at 10%THD, 475W RMS at 5% THD 450W RMS at 10%THD                          |
| Output Regulation     | 2dB, no load to full load at 1kHz                                                                 |
| Input Channels        | 1 × Mic 1mV / 4.7kOhm, 1 × Aux 100mV / 470kOhm, 1 × Aux 250mV / 20kOhm, 1 × Aux 1V / 20kOhm       |
| Frequency Response    | 50Hz-18,000Hz ±3dB                                                                                |
| Signal to Noise Ratio | 60dB                                                                                              |
| Tone Controls         | Bass (100Hz) : ± 8dB, Lo-Mid (315Hz) : ± 8dB, Mid (1kHz) : ± 8dB, Hi-Mid (3.1kHz) : ± 8dB         |
| Line Output           | 1V/1kOhm                                                                                          |
| Speaker Output        | 2Ohm, 4Ohm & 8Ohm                                                                                 |
| Power Supply          | AC: 220-240V 50/60Hz                                                                              |
| Protections           | 2 × 20 Amp fuse in ± DC supply 5 Amp circuit breaker in AC mains, Protected against short circuit |
| Power Consumption     | 1000 VA                                                                                           |
| Dimensions            | W482 × H166 × D435 mm                                                                             |

|        |        |
|--------|--------|
| Weight | 23.5kg |
|--------|--------|

*Specifications from the official Ahuja catalogue. Issued for customer reference.*