

AMX-912

9 Channel

DESCRIPTION :

The Ahuja AMX-912 is a 9-channel PA analog mixer. Input Channels: Each Channel has separate 1/4" balanced phone jack for Mic and Line and accepts both balanced and unbalanced signals.

Echo section provided with Delay, Repeat and Level controls. Tape section for Record and Playback facility.



FEATURES :

- Input Channels: Each Channel has separate 1/4" balanced phone jack for Mic & Line & accepts both balanced & unbalanced signals.
- Mono/Stereo Output: Mono output is available from Left & Right output jacks when the switch is in 'Mono' position.
- Each channel has GAIN, BASS, TREBLE, ECHO, PAN and slide LEVEL controls with CLIP LED indicator.
- Echo section provided with Delay, Repeat & Level controls. Tape section for Record & Playback facility.

SPECIFICATIONS :

Power Requirements	AC: 220-240V 50/60Hz, DC: 24v (2×12V Car Battery)
MIC Input (Impedance/Gain)	2kOhm/62dB
LINE Input (Impedance/Gain)	20kOhm Balanced/42dB, 10kOhm Unbalanced/42dB
Distortion	< 0.08%
Frequency Response	30Hz - 20kHz (+0, -1dB)
Tone Controls	Bass: ±12dB at 100Hz, Treble : ± 12dB at 10kHz
Line Output LO	-10dBm/+2dBm (200mV/1V)
Line Output HI	0dBm/+17dBm (775mV/5.5V)
ECHO/Reverb System	Digital Signal Processing
Signal to Noise Ratio	>70dB (0dBm, 0.775V)
Dimensions	W483 × H93 × D366 mm
Weight	6.7kg

Specifications from the official Ahuja catalogue. Issued for customer reference.