

BTA-1010

PA Amplifier Sets

DESCRIPTION :

Ahuja BTA-1010 is available from MSC, authorized Ahuja dealer for Maharashtra and Goa. Share application (school, temple, retail, events) for specification and quote. The Ahuja BTA-1010 is a 90W Class-D bi-amp PA amplifier sets.

Built-in MP3 player with Bluetooth, Recorder, SD card and Remote Control. Three power source operation AC mains, External 12V DC or built-in 12V 9Ah rechargeable battery.



FEATURES :

- Class D Bi-amplifier featuring attractive, elegant and stylish looking cabinet with Trolley System.
- Two Mic inputs, Two Wireless Mics, one Aux input & one Music input.
- Built-in 38.1 cm (15") 8W speaker with dual voice coil & 8W HF driver.
- Mic 1 has selectable priority over all other inputs.
- Built-in MP3 player with Bluetooth, Recorder, SD card and Remote Control.
- Built-in Digital Echo effects.
- Active Bass & Treble controls for setting the desired tonal quality.
- LED indications for low battery, charging & clip output.
- Facility of Auto cut-off to prevent battery from deep discharge.
- Three power source operation AC mains, External 12V DC or built-in 12V 9Ah rechargeable battery.

SPECIFICATIONS :

Audio Output (BI-AMP)	90W Max.
Input Channels	2 × Mic 3mV/4.7kOhm, 1 × Aux 100 mV/47kOhm, Music 100mV/47kOhm, 2 × Wireless
Preamp Output	200mV/600Ohm
Tone Controls	Bass ±5dB at 100Hz, Treble ±5dB at 10kHz
Digital Player	MP3 player with USB, SD, MMC card reader, Recording Function and Bluetooth.
Power Requirements	AC : 220V-240V 50/60Hz, DC : 12V Car Battery (external), 12V 9Ah Rechargeable
Power Consumption	170VA
Protection	AC Fuse: 1A 250V (T 1A L)
Wireless Receiving Mode	Quartz Controlled Fixed Frequency

Wireless Range	Over 20m in Free Space (Line of Sight)
Dimension	W440 × H700 × D350 mm
Weight	18.80kg
RF Output Power	10mW (Max.)
Max. Modulation	45dB
Frequency Response	50-15,000Hz
Battery	3V (2 × 1.5V AA Pencil Cells)

Specifications from the official Ahuja catalogue. Issued for customer reference.