

BTA-660M

PA Amplifier Sets

DESCRIPTION :

The Ahuja BTA-660M is a 40W PA amplifier sets. Built-in MP3 Player with Bluetooth, Recorder, SD Card and Remote Control. Built-in Digital Echo effects.

Two Mic inputs, Two Wireless Mics, one Aux input and one Music input. Mic1 has selectable priority over all other inputs.



FEATURES :

- Elegant and stylish looking plastic moulded cabinet PA Amplifier Set with Trolley System.
- Two Mic inputs, Two Wireless Mics, one Aux input & one Music input. Mic1 has selectable priority over all other inputs.
- Built-in 203 mm (10") 4Ohm speaker & 8Ohm HF driver.
- Built-in MP3 Player with Bluetooth, Recorder, SD Card and Remote Control. Built-in Digital Echo effects.
- Tone control for setting the desire tonal quality.
- LED indications for low battery, charging & clip output. Auto cut-off feature prevents battery deep discharge.
- Operates on AC mains, external 12V DC or built-in 12V 7Ah rechargeable battery.

SPECIFICATIONS :

Audio Output (BI-AMP)	40W Max. (LF+HF) LF: 25W Max HF: 15W Max
Input Channels	2 x Mic 4mV/4.7kOhm, 1 x Aux 100 mV/47kOhm, Music 100mV/47kOhm, 2 x Wire
Preamp Output	200mV/600Ohm
Tone Controls	Bass ± 5 dB at 100Hz, Treble ± 5 dB at 10kHz
Digital Player	MP3 player with USB, SD, MMC card reader, Recording function and Bluetooth
Power Requirements	AC : 220V-240V 50/60Hz DC : 12V Car Battery (external), 12V 7Ah Rechargeable
Power Consumption	50VA
Protection	AC Fuse: 1A 250V (T 1A L)
Wireless Receiving Mode	Quartz Controlled Fixed Frequency
Wireless Range	Over 20m in Free Space (Line of Sight)
Dimension	W325 x H550 x D280 mm
Weight	14.30kg

RF Output Power	10mW (Max.)
Max. Modulation	45dB
Frequency Response	50-15,000Hz
Battery	3V (2 × 1.5V AA Pencil Cells)

Specifications from the official Ahuja catalogue. Issued for customer reference.