

DPA-770M

75 WATTS WITH BUILT-IN DIGITAL PLAYER

DESCRIPTION :

The Ahuja DPA-770 M is a PA product. Built-in MP3 player with USB reader and remote control.

Line Output for connecting to a Booster Amplifier.



FEATURES :

- 4 Mic & 1 Aux Input.
- Built-in MP3 player with USB reader and remote control.
- Bluetooth facility.
- Line Output for connecting to a Booster Amplifier.
- Cut and Boost type Bass & Treble controls.
- Instant transfer to DC Power (Car Battery) if
- AC power fails.

SPECIFICATIONS :

Power Output	100W Max., 75W RMS at 10% THD, 70W RMS at 5% THD
Output Regulation	2 dB, no load to full load at 1kHz
Input Channels	4 × Mic. 0.6mV/4.7kOhm, 1 × Aux 100mV/330kOhm
Frequency Response	50-15,000Hz ±3dB
Signal to Noise Ratio	55dB
Tone Controls	Bass: -10dB +7dB at 100Hz, Treble: -10dB +7dB at 10kHz
Outputs	Line: 1V/3.5kOhm
Speaker Outputs	4Ohm, 8Ohm, 16Ohm & 100V
Digital Player	MP3 Player with USB, SD, MMC Card Reader & Bluetooth
Power Supply	AC: 220-240V 50/60Hz, DC: 12-14V Car Battery
Power Consumption	AC: 170VA DC: 3A
Dimensions	W385 × H125 × D300 mm
Weight	8.80kg