

FMX-112DP

With built-in MP3 Recorder & Digital Effects



FEATURES :

- 10 MIC, 10 LINE & 01 STEREO Balanced inputs, through 6.3mm (1/4") stereo phone jack socket.
- Built-in digital MP3 player with recording & BT functions.
- Digital Effects channel with DELAY, REPEAT & LEVEL controls.
- Each input channel has a GAIN control, 3 band active EQ controls, AUX, FX and PAN controls.
- The STEREO channel has a GAIN control, 3 band active EQ controls, AUX, FX and PAN controls.
- Each input channel provides Peak LED to indicate excessive input signal levels.
- Each channel has a signal Mute switch and a slide fader control for accurate setting of signal level.
- Selector switch available between Stereo channel (Ch.11/12) & USB playback channel.
- Balanced Left & Right MAIN Mix outputs through M/XLR connectors as well as 6.3mm (1/4") stereo phone jack sockets.
- MONITOR L&R outputs through 6.3mm (1/4") phone jack sockets and individual monitor fader control.
- AUX SEND output with independent level control.
- Headphone output with Phones Control for output monitoring.
- Operates on 240V 50Hz AC mains.

SPECIFICATIONS :

Impedance/Gain	2kOhm Balanced/65dB
THD	<0.1%
L/R Line Output	25Hz - 20kHz (+0, -1dB)
TREBLE/MID/BASS	±12dB at 12kHz/2.5kHz/80Hz
CLIP LED INDICATION	4 dB prior to true clip
Nominal/Max Level	4dBu/21dBu (1.22V/9V)
Impedance	600Ohm
DELAY SYSTEM	Digital Signal Processing
DELAY RANGE SETTINGS	Variable from 20 to 300ms
DIGITAL PLAYER	MP3 Player/Recorder with USB Reader, Bluetooth

HEADPHONE OUTPUT	200mV at 8Ohm, THD <1%
MONITOR OUTPUTS (L&R)	1.6V
SIGNAL TO NOISE RATIO	>80dB
POWER SUPPLY	AC: 220-240V, 50/60Hz
DIMENSIONS	W520 × H105 × D350mm
WEIGHT	5.20kg

Specifications from the official Ahuja catalogue. Issued for customer reference.