

SSB-60EM

MEDIUM WATTAGE PA MIXER AMPLIFIER

DESCRIPTION :

The Ahuja SSB-60 EM is a 60W medium wattage PA mixer amplifier. Preamplifier Output for connecting to a Booster Amplifier and for recording the programme.

Instant transfer to DC power (Car Battery) if AC power fails.

FEATURES :

- 4 Mic & 1 Aux Inputs.
- Preamplifier Output for connecting to a Booster Amplifier and for recording the programme.
- Instant transfer to DC power (Car Battery) if AC power fails.
- Cut type Bass & Treble Controls.



SPECIFICATIONS :

Power Output	90W Max., 65W RMS at 10% THD, 60W RMS at 5% THD, 50W RMS at 2% THD
Output Regulation	2 dB, no load to full load at 1kHz
Input Channels	4 × Mic 0.65mV/4.7kOhm, 1 × Aux 100mV/470 kOhm
Frequency Response	50-15,000Hz ±3dB
Signal to Noise Ratio	60dB
Tone Controls	Bass: -10dB at 100Hz, Treble: -10dB at 10kHz,
Speaker Outputs	4Ohm, 8Ohm, 16Ohm & 100V
Power Supply	AC: 220-240V 50/60Hz, DC: 12V (12V Car Battery)
Power Consumption	AC: 160VA DC: 3A
Dimensions	W350 × H120 × D265 mm

Specifications from the official Ahuja catalogue. Issued for customer reference.