

TZA-1200

2 ZONE PA MIXER AMPLIFIER

DESCRIPTION :

The Ahuja TZA-1200 is a 120W 2 zone PA mixer amplifier. TZA-1200 is suitable for small sized installations such as in places of worship where both external and internal speakers are required to be connected with different sound level settings.

Connecting two groups of speakers, preamplifier output, bass and treble controls, zone On/Off facility, AC/DC operation have been provided.



FEATURES :

- 5 Mic & 2 Aux Inputs.
- 60W+60W power output.
- Connecting two groups of speakers, preamplifier output, bass and treble controls, zone On/Off facility, AC/DC operation have been provided.
- TZA-1200 is suitable for small sized installations such as in places of worship where both external and internal speakers are required to be connected with different sound level settings.

SPECIFICATIONS :

Power Output	90W + 90W Max., 60W + 60W RMS at 10% THD, 55W + 55W RMS at 5% THD, 5
Output Regulation	2 dB, no load to full load at 1kHz
Input Channels	5 × Mic 0.6mV/4.7kOhm, 1 × Aux 100mV/470 kOhm, 1 × Aux 200mV/250kOhm (R
Frequency Response	70-15,000Hz ±3dB
Signal to Noise Ratio	60dB
Tone Controls	Bass: -10dB at 100Hz, Treble: -10dB at 10kHz
Outputs	Preamp 200mV/600Ohm
Speaker Outputs	4Ohm, 8Ohm, 16Ohm & 100V for each zone
Power Supply	AC: 220-240V 50/60Hz DC: 12V (12V Car Battery)
Power Consumption	AC: 250VA DC: 5A
Dimensions	W400 × H130 × D290 mm
Weight	10.1kg