

UBA-800DP

DJ & PA POWER AMPLIFIER



FEATURES :

- Bass and Treble controls provided for precise and accurate tonal setting of the programme.
- Line Input and Line Output have been provided to enable interconnections with other power amplifiers.
- Circuit Protector Device has been provided which safeguards the amplifier against overload and short circuit.
- Indicator LEDs for Power, Signal, Temp, Overload and Fault conditions have been provided.
- 20hm speaker matching provided in addition to 4 & 80hm.

SPECIFICATIONS :

Power Output	1150W RMS Max., 800W RMS at 10%THD, 770W RMS at 5% THD 725W RMS a
Output Regulation	2dB, no load to full load at 1kHz
Input Channels	1 × Mic 1mV / 4.7kOhm, 1 × Aux 100mV / 470kOhm, 1 × Aux 250mV / 20kOhm, 1
Frequency Response	50Hz-18,000Hz ±3dB
Signal to Noise Ratio	60dB
Tone Controls	Bass (100Hz) : ± 8dB, Treble (10kHz) : ± 8dB
Line Output	1V/1kOhm
Speaker Output	20hm, 40hm & 80hm
Digital Player	MP3 Player with USB, SD, MMC Card Reader & Bluetooth
Power Supply	AC: 220-240V 50/60Hz
Protections	2 × 25 Amp fuse in ± DC supply 8 Amp circuit breaker in AC mains Protected again
Power Consumption	1500 VA
Dimensions	W482 × H186 × D530 mm
Weight	32.0kg

Specifications from the official Ahuja catalogue. Issued for customer reference.