

UTR-30E

LOW WATTAGE PA MIXER AMPLIFIER

DESCRIPTION :

The Ahuja UTR-30E is a 25W low wattage PA mixer amplifier. Extremely portable and ideal for use in remote places without electricity.

It has a battery saver switch for long battery life and red led for low battery indication.



FEATURES :

- 3 Mic & 1 Aux Input.
- Cut type Tone control.
- 3 POWER SOURCE Amplifier: AC mains, 12V DC (Car Battery) and 12V DC Dry Cell (Two Banks of 8×1.5V UM-1 cell each).
- Extremely portable and ideal for use in remote places without electricity.
- Battery saver switch for long battery life and red LED for low battery indication.

SPECIFICATIONS :

Power Output	35W RMS Max., 25W RMS at 10% THD,
Input Channels	3 × Mic 1.0mV/10kOhm, 1 × Aux 50mV/250kOhm
Frequency Response	150-10,000Hz ±3dB
Signal to Noise Ratio	60dB
Tone Controls	-15dB at 10kHz
Speaker Outputs	4Ohm, 8Ohm & 16Ohm
Power Supply	AC: 220-240V 50/60Hz, DC: 12V (Car Battery), DC: 12V (Dry Cells 8 × UM-1 Two
Power Consumption	AC: 80VA DC: 1.2A
Dimensions	W250 × H115 × D270 mm
Weight	4.3kg

Specifications from the official Ahuja catalogue. Issued for customer reference.