

X 25

3 channel DJ mixer

DESCRIPTION :

The X 25 is a 3 channel DJ mixer with a built-in USB MP3 media player & recorder, Bluetooth, audio interface, 3-band kill EQ (-30 dB) and multiple inputs and outputs to let you mix in style.



FEATURES :

- 3-band kill EQ (-30 dB) and gain control per channel.
- Balanced XLR mic input with gain and 3-band EQ.
- Built-in USB MP3 media player with wireless Bluetooth connectivity.
- PC USB audio interface for playback and recording via media player.
- Crossfader flat / steep curve switch.
- Headphone cue Mix with blend switch.
- 14" headphone output with level control.
- Separate booth RCA output.
- Balanced XLR master output.
- Ultra smooth and sturdy faders.

SPECIFICATIONS :

Series	X Series
Gain (Mic / Phono / Line)	40dB / 0dB
Input Level Sensitivity (Mic / Phono / Line)	-40dB / 0dB
Main Output Levels (Nominal / Max)	0dBu (0.775V) / +18dBu (6.15V RMS)
Booth Output Levels (Nominal / Max)	0dBu (0.775V) Nominal / +18dBu (6.15V RMS) Max
Frequency Response	20Hz-22KHz (+/-3dB)
Total Harmonic Distortion	0.07% @ 1KHz 0.1% @ 1KHz
Equalisation Line I/P (Treble/Mid/Bass)	Line: +10/-12dB @ 10kHz, +12/-24dB @ 1.3kHz, +12/-29dB @ 50Hz, Mic: ±12dB
Signal to Noise Ratio (Mic/Line)	65dB / 82dB
Dimension (W x D X H) mm	198 x 294 x 104
Net Weight (Kg)	2.3

Specifications from the official SM Professional literature. Issued for customer reference.