

X 55

5 channel DJ mixer

DESCRIPTION :

The X 55 is a 5 channel DJ mixer with a built-in USB MP3 media player & Bluetooth, 3-band kill EQ (-30 dB) and multiple inputs and outputs to let you mix in style.



FEATURES :

- 3-band kill EQ (-30 dB) and gain control per channel.
- Balanced XLR mic input with gain and 3-band EQ.
- Built-in USB MP3 media player with wireless Bluetooth connectivity.
- Crossfader flat / steep curve switch.
- Headphone cue Mix with blend switch.
- Separate master, record and booth RCA output.
- ¼" headphone output with level control.
- Balanced XLR master output.
- Ultra smooth and sturdy faders.

SPECIFICATIONS :

Series	X Series
Gain (Mic / Phono / Line)	40dB / 40dB / 0dB
Input Level Sensitivity (Mic / Phono / Line)	-40dBu / -40dBu / 0dBu
Main Output level (Nominal / Max)	0dBu (0.775V) / +18dBu (6.15V RMS)
Booth Output Levels (Nominal / Max)	0dBu(0.775V) Nominal / +18dBu(6.15V RMS) Max
Frequency Response	20Hz-22KHz (+/-3dB)
Total Harmonic Distortion	0.07% @ 1KHz 0.1% @ 1KHz
Equalisation Line I/P (Treble/Mid/Bass)	+10/-12dB @ 10kHz
Signal to Noise Ratio (Mic/Line)	65dB / 82dB
Dimensions (W x D x H) mm	277 x 300 x 105
Net Weight (Kg)	3

Specifications from the official SM Professional literature. Issued for customer reference.